



LINK ELECTRIC & SAFETY CONTROL CO.

444 McNally Drive, Nashville, TN 37211

(615)-833-4168 FAX (615)-834-1984

info@linkelectric.com

Nema Starter Sizes based on Motor Horsepower and Voltage				
HP/VAC	208 Volt	230 Volt	460 Volt	575 Volt
2	Size 1	Size 1	Size 1	Size 1
3	Size 1	Size 1	Size 1	Size 1
5	Size 1	Size 1	Size 1	Size 1
7.5	Size 2	Size 1	Size 1	Size 1
10	Size 2	Size 2	Size 1	Size 1
15	Size 3	Size 2	Size 2	Size 2
20	Size 3	Size 3	Size 2	Size 2
25	Size 3	Size 3	Size 2	Size 2
30	Size 4	Size 3	Size 3	Size 3
40	Size 4	Size 4	Size 3	Size 3
50	Size 5	Size 4	Size 3	Size 3
60	Size 5	Size 5	Size 4	Size 4
75	Size 5	Size 5	Size 4	Size 4
100		Size 5	Size 4	Size 4
125			Size 5	Size 5
150			Size 5	Size 5

Note: this chart has been revised to require a Size 2 starter for 7.5 HP @208VAC. Press controls built for 7.5HP main flywheel motors @208VAC will typically have a 60 Amp MC Switch. This is a departure from the NEMA tables, but is typically needed due to the startup requirements for these motors in press applications.